

# **Failure Analysis System Procedure**

# DOC Submersible Electric Pumps



#### 1) Electric pump applications

- Emptying of residential sump pits or rainwater tanks
- · Emergency draining of flooded basements and garages.
- Transfer of water from tanks, cistems and swimming pools.
- · Garden and lawn irrigation.

#### 2) Critical items of application

### 2.1) Electrical supply

- In running condition, supply voltage must be into tolerance values ± 5%:
- a too high voltage generates overheating and overload;
- a too low voltage, generates starting problems.
- In starting operation, max drop voltage 5%:
  - a too high drop voltage generates starting problems.
- Max starting frequency 40 start/h:
  - if starting frequency is greater than limits, it generate overheating or overload problems.

1



#### 2.2) Liquid

- Max liquid temperature with pump partially submersed 40 °C:
- if temperature is greater than max value, it generate overheating in motor.
- Max diameter of solids in suspension:
- DOC 3, DOC 7 pump: 10 mm;
- DOC 7VX pumps: 20 mm;
- solid parts with diameters greater than limits, damages hydraulic part (stoppages) and motor (overload/overtemperature).
- DOC 7VX (with VORTEX impeller) can pump water with suspended solid and filaments.
- Pumping of abrasive liquid generate a rapid wear of impeller.
- Pump must not pump hydrocarbons or danger liquids.
- Liquid must not be brackishwater, seawater or corrosive:
- corrosions are caused by incorrect applications (inadequate ground system, leakage current, stray current, unsuitable pumped liquid...) and they cannot be inputed to product or constructive materials.

#### 2.3) Installation

- Max depht of immersion: 5 m.
- Pump must not operate 24h/24h; otherwise it generates overheating of the motor.
- Pump must not handled with the supply cable, but only with the handle; otherwise the cable can disjoin.
- If the pump is installed inside of a sump pit, his dimensions must be so that to avoid continous start and stop of the pump; otherwise, the motor is subjected to overheating.
- If the pump is installed in a fixed installation, it is advised a positioning with a min high of 10 cm from the floor to avail the water decantation. Otherwise it generate a rapid wear of impeller.
- If the pump is not installed in a fixed installation and it is used to drain a little room, it can positioned on the foor.
- The pump must never work in dry condition.
- Lenght of float cable must not be modified and it necessary check the fixing of the cable. Changing of cable lenght generates continous start and stop or dry working of pump.
- The pump must be positioned so that to let the float to move without obstacles (see the draw in the installation handbook).
- GT version (fixed float) must pump only clean water and not stagnant to guarantee its correct working.
- 1~ motors have an internal motor protection but they cannot operate without a operator supervision or insertion of additional protections inside of control board.
- 3~ motors must be protected with a circuit breaker installed by a Customer (it is adviced use of Lowara control board).
- It is recommended installation of high sensibility differential switch ( $I\Delta n \le 0.03$  A) inside of control board, to protect the people from possible electric contact with live parts.

2



#### 3) Equipments and tools required

- Megaohmeter 500 1000 Vdc;
- Threaded clutch (code 160600400) for test of pneumatic seal (see picture).



# 4) Inspection of defected product

## 4.1) Preliminary information

On receiving of defective product, requirements from Customer:

- purchase date (if possible, confirmed by bill or sale slip);
- · installation date;
- installation handbook:
- · conditions of installation.

#### 4.2) External visual inspection

External condition of product

Corrosion on metal surface or on welds (with little holing) or overtemperature (motor sleeve with brown/blue colour) are an indication of incorrect or unsuitable use (see 2.1, 2.2, and 2.3) and exclude an acknowledgment of technical warranty.

Product analysis stop and repair (if required) is done for a fee.

If there are not elements of objection, go on with inspections in 4.3.

## 4.3) Preliminary inspections

- Data in plate:
- type of product and code;
- series number;
- manufacturing date;

NOTE WELL: if rating plate on the pump is illegible or lost, it can found in one copy in installation booklet or, if installed, on control board door.

- · Presence and condition of:
- whole supply cable;
- float;
- test screw of pneumatic seal on head and his O-Ring;
- · Welds and possible dents in the jacket.

# 4.4) Electrical resistence of windings

• Measure electrical resistance of windings to check the possible presence of interruption or burning.

3



#### 4.5) Measure of insulation resistance

Performed in accordance with european standard EN 602 04-1 (500 Vdc between conductors and ground). Test is passed if insulation resistance is  $\geq$  10 M $\Omega$ .

Lower values of 10  $M\Omega$  are indicative of insulation breakdown (with probable water infiltration), therefore is necessary pneumatic seal test (see 4.6).

NOTE WELL: if pneumatic seal test does not indicate leaks, is necessary unconnect all electrical parts (supply cable, wound stator and float if presente), and repeat the measure of insulation resistance on singular components.

# 4.6) Pneumatic seal test

- Blow in compressed air 0.6 bar in test hole on higher head with help of threaed clutch.
- NOTE WELL: pressures greater than 0.6 bar can generate damage to components and people.
- With pump immersed in water check absence of air balls from: delivery side, presscable plaques, bottom and welds.
- If pneumatic seal test not indicate leaks, see NOTE WELL in 4.5.

# 5) Disassembly and analysis

N.W. The pictures refers to a DOC 3 pump

- Remove the lower cover and the suction grid (DOC 3, DOC 7) or remove the fixing screw and the lower support (DOC 7VX) and check:
- presence or not of solid parts can have obstructed the pump.
- Remove the stop ring and exctract the impeller:
- check the conditions of the impeller and condition of V-Ring inserted on the hub.
- Unscrew the tie-rods and remove the external sleeve checking:
- its integrity;
- condition of welds;
- condition of O-Ring.





- Detach the upper head from the stator and check:
- condition of O-Ring;
- condition of capacitor;
- connection in the terminal board;
- check the possible presence of water or deposit witch indicates a infiltration of water through O-Ring or presscable.



- Detach the pump body and the rotor from the stator and examine:
- the condition of intenal surface of pump body;
- the condition of rotor bearings;
- the possible corrosion of lower part of the shaft.



- Performe a heads visual analysis of stator to find possible problems with following cases:
- a) all motors:
- one or more winding coils burnt ----> shorted coil;
- b) 1~ motor:
- run winding OK and start winding KO ----> capacitor defected;
- run winding KO and start winding OK ----> motor could not start;
- both windings faulty ----> overload;
- c) 3~ motor:
- 1 phase fine and 2 phases burnt ----> powered with only 2 phases;
- all phases burnt ----> overload;







# 6) Checl list

T <u>ype</u> of problem		Pump data
	Does not delivery water	Type:
	Low performance	Code:
	Does not starts	Series number:
	Does not stops	Installation date:
	Starts and stops too frequently	Manufacturing date
	Noisy	Liquid pumped:
	Grounded motor	Temperature:
	Excessive power input	Note:
	Runs slowly	
	Further:	

DOC pumps failure causes required for claim opening

What 100 Flooded/full of water	Why 106 Uncorrect assembly/testing of components	
100 1 100ded/1dil of Water		
	110 holes of drain condensate, obstructed/closed	
	111 Pinched gasket screws	
	112 Not complying components tooling	
	17 0 1	
	, , , , , , , , , , , , , , , , , , , ,	
	119 Normal wear	
	120 Excessive wear	
	101 Further:	
101 Excessive power input /	102 Motor shaft locket	
	104 Wrong internal electrical connections	
January Carrie		
	108 Short circuit for contact with mobile parts	
	109 Short circuit between coils/windings	
	, , ,	
	1,0	
	<u> </u>	
	101 Further:	
102 Runs slowly / does not st	106 Uncorrect assembly/testing of components	
103 Does not stops	105 Defected/not operating electrical/electronic components	
	1 9	
	, , , , , , , , , , , , , , , , , , , ,	
104 Noisy / locked / vibrate		
(ok windings)		
<u> </u>		
		1
	119 Normal wear	
	120 Excessive wear	
_	103 Does not stops  104 Noisy / locked / vibrate	120 Excessive wear   101 Further:   102 Motor shaft locket   102 Motor shaft locket   104 Wrong internal electrical connections   106 Uncorrect assembly/testing of components   107 Bursted / unconnected capacitor   108 Short circuit for contact with mobile parts   109 Short circuit between coils/windings   114 Hydraulic rotating part locked   115 Presence of external matters between windings   100 Further (supply detailed description of failure)   121 Inadequate power supply   103 Not complying/unsuitable applications   115 Inadequate size of motor   116 Inadequate cooling   119 Normal wear   120 Excessive wear   101 Further:   102 Runs slowly / does not st   106 Uncorrect assembly/testing of components   107 Bursted / unconnected capacitor   117 Defected/wrong rotor   118 Not operating level sensors   109 Further (supply detailed description of failure)   121 Inadequate power supply   103 Not complying/unsuitable applications   113 Inadequate size of motor   101 Further:   101 Further:   102 Locked / vibrate   106 Uncorrect assembly/testing of components   107 Further:   108 Defected/not operating electrical/electronic components   118 Not operating level sensors   100 Further:   101 Further:   101 Further:   102 Locked motor shaft   106 Uncorrect assembly/testing of components   101 Further:   102 Locked motor shaft   106 Uncorrect assembly/testing of components   107 Further:   108 Locked motor shaft   108 Uncorrect assembly/testing of components   109 Uncorrect assembly/testing of components   109 Uncorrect assembly/testing of components   109

6



- natt / toothing lift		
Shaft / toothing jut	112 Not complying components tooling	
	100 Further (supply detailed description of failure)	
	103 Not complying/unsuitable applications	
401 Broken/cracked		
200 Not operate	· · ·	
	118 Not operating level sensors	
	119 Water full level sensors	
	100 Further (supply detailed description of failure)	
	121 Inadequate power supply	
	103 Not complying/unsuitable applications	
	119 Normal wear	
	120 Excessive wear	
	101 Further:	
300 Low performance	106 Uncorrect assembly/testing of components	
Jose Law parisonnance		
104 Noisy / locked / vibrate		
104 Noisy / locked / Vibrate		
	100 Further (supply detailed description of failure)	
	103 Not complying/unsuitable applications	
	103 Not complying/unsuitable applications 119 Normal wear	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
400 Look	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further:	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure)	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further:	
400 Leak 400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure)	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further:	
	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further:	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 119 Normal wear 120 Excessive wear	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure)	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear	
400 Leak	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
400 Leak  401 Broken/cracked	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
400 Leak  401 Broken/cracked  600 Wrong rating plate	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
400 Leak  401 Broken/cracked  600 Wrong rating plate packing	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components	
400 Leak  401 Broken/cracked  600 Wrong rating plate packing 601 Wrong product	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear	
400 Leak  401 Broken/cracked  600 Wrong rating plate packing	103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components 112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 106 Uncorrect assembly/testing of components	
	401 Broken/cracked  200 Not operate  300 Low performance	119 Normal wear 120 Excessive wear 101 Further:  112 Not complying components tooling 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further:  200 Not operate  105 Defected/not operating electrical/electronic components 200 Lack of technical / commercial information 118 Not operating level sensors 119 Water full level sensors 100 Further (supply detailed description of failure) 121 Inadequate power supply 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further:  300 Low performance  106 Uncorrect assembly/testing of components 119 Normal wear 120 Excessive wear 100 Further (supply detailed description of failure) 103 Not complying components tooling 300 Wrong rating plate/packing 100 Further (supply detailed description of failure) 103 Not complying/unsuitable applications 119 Normal wear 120 Excessive wear 101 Further: 104 Noisy / locked / vibrate  105 Locked / vibrate 106 Uncorrect assembly/testing of components 112 Not complying components tooling 114 Hydraulic rotating part locked

7



# 9) Faq

Power supply problems:	Problem founded	Possible causes of the problem
• unconnected cable or damaged; • supply voltage too low; • starting drop voltage too high; Fuses burnt. Circuit breaker not calibrated. Capacitor too small or damaged (1~). 2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input	Pump does not start	Power supply problems:
• supply voltage too low; • starting drop voltage too high; Fuses burnt. Circuit breaker not calibrated. Capacitor too small or damaged (1~). 2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		• no power;
- starting drop voltage too high; Fuses burnt. Circuit breaker not calibrated. Capacitor too small or damaged (1~). 2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		<ul> <li>unconnected cable or damaged;</li> </ul>
Fuses burnt. Circuit breaker not calibrated. Capacitor too small or damaged (1~). 2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic Starts and stops too frequently Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		<ul> <li>supply voltage too low;</li> </ul>
Circuit breaker not calibrated. Capacitor too small or damaged (1~). 2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		<ul> <li>starting drop voltage too high;</li> </ul>
Capacitor too small or damaged (1~). 2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		Fuses burnt.
2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic Starts and stops too frequently Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		Circuit breaker not calibrated.
2 phases powered (3~). Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic Starts and stops too frequently Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		Capacitor too small or damaged (1~).
Activation of float. Hydraulic locked (solid parts between the impeller and the suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		, ,
Suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Suction flange) Faulty stator.  Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		Hydraulic locked (solid parts between the impeller and the
Pump does not delivery water  Delivery outlet obstructed Water level too low Filter obstructed  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Water level too low Filter obstructed  Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input	Pump does not delivery water	Delivery outlet obstructed
Low performance  Delivery outlet obstructed Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		Filter obstructed
Water level too low System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input	l ow performance	Delivery outlet obstructed
System leaks Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Dirty filter Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Wear of hydraulic part Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Pump run in the opposite way Wrong pump, undersized O-Ring damaged  Noisy  Motor bearings damaged Unbalanced hydraulic  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Noisy  Motor bearings damaged Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		
Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input		O-ning damaged
Unbalanced hydraulic  Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input	Noisy	Motor bearings damaged
Starts and stops too frequently  Float damaged or wrong regulated Sump pit too small Pump or pipes obstructed Excessive power input	l	
Sump pit too small Pump or pipes obstructed Excessive power input		Official five a five autic
Pump or pipes obstructed  Excessive power input	Starts and stops too frequently	Float damaged or wrong regulated
Excessive power input		Sump pit too small
Excessive power input		Pump or pipes obstructed
Leaks in system		Excessive power input
		Leaks in system
Runs slowly Run and start windings exchanged on control panel (1~)	Runs slowly	Run and start windings exchanged on control panel (1~)
Wrong windings connections inside the motor (3~)	<b>,</b>	• • • • • • • • • • • • • • • • • • • •
Grounded motor Grounded supply cable or jack	Grounded motor	Grounded supply cable or iack
Grounded float cable		
Water infiltration:		
• through test holes;		
• rupture of pump body;		
• shaft scored;		
• O-ring pinched or cut;		
• seal rings not lubricated or reverse assembling.		
searnings not lubricated or reverse assembling.		- searnings not indirected of reverse assembling.


8



Excessive power input	Uncorrect voltage Windings defected Motor supplied with 2 phases instead of 3 (3~ motor) Overload
Faulty stator	Lightning discharge inverter or overvoltage Overheating Overload
LEAKS OF HYDRAULIC PART	O-Ring pinched or cut External sleeve broken
Presence of water in the motor	Test screw lacking Rupture of pump body O-ring out of seat or cut Shaft scored Seal rings not lubricated or reverse assembled
Hydraulic locked	Liquid unsuitable Presence of foreign matters between the impeller and the suction flange.
Overheating/overload	Liquid unsuitable. Motor thrust bearings damaged Too high frequency of startings Supply voltage uncorrect Defected pump Pump operated for a time too long

inverter or overvoltage

Overheating / overload



# 8) Failure tree: hydraulic part (DOC pumps)

